



ATTENTION

Please read the instructions carefully before using this product

warning: In order to reduce the risk of fire or electric shock, please do not put the equipment in the rain or wet place.
Note: please do not disassemble the equipment without permission. There is no part that can be repaired by the user. Please hand it over to qualified maintenance personnel

- 1 Please use the attached charging line for charging. If you are unsure of the type of power available, please consult your dealer.
- 2 The device has a built-in lithium battery. Please do not put it into the fire or near the heat source.
- 3 This equipment is not waterproof, do not put into water or other liquids.
- 4 Please do not attempt to repair the equipment, because open the lid after may make you touch the danger point voltage or other risks. If this equipment is the need for maintenance, please to qualified maintenance personnel for repair.
- 5 If you are not using this product for a long time, you should unplug the charging cable.
- 6 Avoid the power cord being trampled or the position of the socket and the connecting device being too tight at the plug.

PRODUCT INTRODUCTION

SWIFF AUDIO®
A10R Rechargeable Clip-On Mini Tuner

The A10R Tuner is SWIFF AUDIO's innovative mini tuner. Its incredibly small size enables fast and accurate sound correction while also having a very clear, wide, borderless LED curved display, ensuring that our users can achieve perfect viewing angles and screen clarity in any lighting condition. A10R built-in lithium battery with Type-C charging interface, through the attached charging cable connected to the USB charging device to charge the product, each time full can be used for 24 hours.

SPECIFICATION

Tuning mode	Twelve-equal law
Calibration range	A0(27.50Hz)-B8(4186Hz)
Pickup mode	Vibration pickup
Reaction rate	≤ 20 milliseconds
Calibration progress	± 1 tone fraction
Battery	3.7V (Polymer lithium battery) 120mAh(0.44Wh)
Dimension	35mm*40mm*16mm

* The size data is manually measured, and there is some error. Please refer to the actual data.

Function introduction

Instructions for use

1. Please clamp the tuner as close as possible to the position where the vibration of the instrument to be tuned is strongest.
2. Press the power button to power on/off.
3. After the device is powered on, the red pointer on the far left of the screen indicates that the product is in the state of sound correction.
4. When correcting the sound, the pointer on the left of the sound name is low, while the pointer on the right of the sound name is high. When the sound name and the nearest green pointer on both sides are displayed at the same time, it is calibration.
5. In order to save battery power, when there is no vibration signal input, the display will automatically shut down after 5 minutes. If you need to continue using the display, please press the power button to wake up.

Charging instructions

Adapter parameter 5V 1A

Charging state	Discharge state
<75% The red light is blinking	Turn off 5 seconds after the green light is on
75% - 100% green blinking	The red light is steady on in 30% - 5%
100% green on	<5% The red light blinks

A10R Rechargeable
Clip-On Mini Tuner

Manufacturer: SWIFF Technology Co., Ltd.
Manufacturer Address: Longhua, SZ 518109 CHINA
Tel: +86 755 2331 1770
Website: www.swiffaudio.com

MADE IN CHINA